

FR SKY

Xact Series Servo

Dynamic Integrated Performance

FrSky Electronic Co., Ltd.



	HV5101	HV5201	HV5202	HV5203	HV5301	HV5401	HV5402	HV5403
Photo/Style								
Weight (g)	18	23	23	23	41	72	72	72
Size (mm)	28*8*29	23*12*29	23*12*29	23*12*29	35*15*31	40*20*39	40*20*39	40*20*39
Torque (kgf.cm) ±15%@8.4V	6.8	4.2	4.8	8.2	6.1	8.7	14.8	26.2
Speed (S/60°) ±12%@8.4V	0.10	0.04	0.06	0.08	0.08	0.04	0.08	0.11

	HV5404	HV5405	HV5501	HV5502	HV5601 5611	HV5602 5612
Photo/Style						
Weight (g)	72	72	58	58	9.5	9.5
Size (mm)	40*20*39	40*20*39	41*20*27	41*20*27	23*8*19	23*8*19
Torque (kgf.cm) ±15%@8.4V	32.0	36.8	19.3	11.2	4.1	4.1
Speed (S/60°) ±12%@8.4V	0.13	0.19	0.11	0.07	0.05	0.05

About F.Port 2.0:

Working with the F.Port 2.0 protocol, the telemetry data (like real-time current and voltage) of Xact servos can be achieved and transmitted back to the radio by connecting either F.Port 2.0 capable receiver or flight controller. All the preset servo options of speed and torque can be configured directly on an ACCESS radio through the host device of F.Port 2.0 line, and the configurable servo steering as well as travel degree are additions now can be expected on this series.

More information:



Features

- Digital High Resolution Magnetic Sensor*
 - * HV5611/5612: Potentiometer Sensor
- Full Metal Gears
- All Aluminum Housing by CNC
- Programmable by F.Port 2.0/Telemetry by F.Port 2.0
- Firmware Update
- 4.8-8.4V Supported
- Operating travel: 360°

* About the shell color, please refer to the actual product.

86-510-8518 7718

 frsky@frsky-rc.com

 www.frsky-rc.com

 F-4, Building C, Zhongxilu Technology Park, No.3

 Yuanxi Road, Wuxi, 214125, Jiangsu, China